

Get **Kanjoos** with your **time, cost and effort.**

Now print **5 pages** at the **cost of 1**

Presenting
SP 111SU
The **JAM FREE**
multi-function
printer for
everyday use.

Genuine Refill™
PROGRAM

Only on SP 100, SP 111, SP 200 & SP 210 Series

SP 111SU

- Print / Scan / Copy
- Print / Copy Speed: 16 PPM
- Resolution: 1200 x 600 dpi
- Duplex: Manual
- Duty Cycle: 10,000 Pages
- Colour TWAIN Scanner
- Genuine Refill
- World's Best Jam-Free Multifunction Printer



Proud to be a

Kanjoos Much-in-use!



Refill Method.
*Suggested 2 Refills
per Cartridge



SMS: "RICOH" to 57272
Website: www.ricoh.co.in
Email: LP@ricoh.co.in

RICOH SP 111/SP 111SU

MAIN SPECIFICATIONS

GENERAL

Configuration:	Desktop
Warm-up time:	25 seconds
First output time:	13 seconds
Print speed (A4):	16 pages per minute
Memory:	16 MB
Duty Cycle:	10,000 pages
Dimensions (W x D x H):	402 x 368.5 x 119 mm/ 402 x 368.5 x 163 mm
Weight:	6.7/ 8.5kg
Power source:	220 - 240 V

PRINTER

Printer language:	Standard: DDST (GDI)
Print resolution:	1,200 x 600 dpi
Interface: Standard:	USB 2.0
Windows® environments:	Windows® XP Windows® Vista Windows® 7 Windows® 8 Windows® Server 2003 Windows® Server 2008 Windows® Server 2012

COPIER (SP 111SU)

Copying process:	Laser beam scanning and electrophotographic printing
Multiple copying:	Up to 99 copies
Resolution:	300 x 600 dpi 600 x 600 dpi
Zoom:	From 25% to 400%

SCANNER (SP 111SU)

Resolution:	Maximum: 600 dpi
Original size:	A4
Bundled drivers:	TWAIN
Scanning:	Colour scan, 24 bit

PAPER HANDLING

Recommended paper size:	Bypass tray: A4, A5, A6, B5, B6, Legal size
Paper input capacity:	Standard: 50 sheets
Paper output capacity:	Maximum: 10 sheets
Paper weight:	60 - 105 g/m ²

ECOLOGY

Power consumption:	Average: 300 W
Low power mode:	60 W
Sleep mode:	5 W

CONSUMABLES

Tone Yield : Standard :	2,000 pages
Refill Yield* :	2,000 pages per Refill pouch

*Suggest Refill maximum 2 times per toner cartridge.
Post 2 times Refill, discard the cartridge.

*As per ISO/IEC19752 standard

For availability of models, options and software, please consult your local Ricoh representative.

RICOH

Genuine Refill
PROGRAM
Only on SP 100, SP 111, SP 200 & SP 210 series



SMS: "RICOH" to 57272
Website: www.ricoh.co.in
Email: LP@ricoh.co.in

Service Toll Free No: 18001030066 / 1800116600



For more information, please contact:

Please log on to our e-store www.ricohstore.co.in for our other product portfolio